

Linortek Netbell®-2-2Buz Extra Loud Network Break Buzzer Kit

Applications

Provide remote access to control timed alert system for:

- Factories
- Office Buildings
- Warehouses
- Any other places need a timed alert system for breaks, shift changes or general alarms

The Key Features

- Network enabled, access the Netbell from any computer on the network
- All-in-one system, no additional software or designated computer required
- Import/export schedules from existing data in text format
- Flexible and accurate control of when the bells ring (HH:MM:SS,MM/DD/YYYY, SUNDAY- SATURDAY)
- Built-in real time clock sync its time from NTP server every 30 minutes (user changeable)
- Built-in rechargeable battery protected auxiliary real time clock
- Use as either a network device or a standalone device
- Designed, developed and built in the USA with global materials

Self-Contained, Easy-To-Use, Remote Access, Scheduling Buzzers Over the Network, No Additional Software or Designated Computer Required



Linortek Netbell® is an ease-of-use, network enabled, custom developed device for schools, factories, warehouses and other organizations to build a fully automated web-based timed alert system for signaling shift changes, general alarm, and breaks in areas of high ambient noise levels. The system is built on a TCP/IP platform with a built in web server, which allows users to access, control, and schedule the Bells or buzzers accurately and effectively using an Internet connection from anywhere over the network, with no additional software or designated computer required.

The Netbell-2-2Buz is a one-stop solution that comes with everything needed for installation and operation a buzzer system. The kit includes one Netbell-2 networked bell controller, two extra loud buzzer kits (volume adjustable). Each buzzer kit comes with one 4-inch buzzer, one weatherproof back box for wall mounting and one 24VAC power supply to power the buzzer, one 10ft power cable. With the Netbell-2, you can access, control and schedule bells individually over the network, no additional software or programming required. With the digital input you can wire a push switch for ringing buzzers manually in emergency.

For anyone who has separate areas or multiple buildings where running additional wiring is not an option, but network is available at the locations, you can use the built-in remote feature to manage & schedule multiple Netbell devices from one easy-to-use interface, without the need of hard-wiring the bells to a central control station, making the management of your bell systems incredibly easy.

Netbell® Technical Specifications

Netbell-2 DIY Buzzer Kit

General Information		
Model	Netbell-2-1Buz	Netbell-2-2Buz
Part#	01-910-00026	01-910-00028
Technical Specification		
Web Server	Built- In (All software located on built-in web server.)	
Event Schedules	Up to 500 Web-Based Event Schedules (Add schedules from web browser)	
Bell Ringing Duration	User Programmable for Each Schedule	
Built-In Bell/Buzzer	No	
Bell Output(s)	2	
External Buzzer(s)	1 (4" Buzzer,110dBa@ 1m)	2 (4" Buzzer,110dBa@ 1m)
Coverage (SQ FT)	25000	50000
Manual Bell Control	Yes	
Push Switch	Not Included	
Enclosure	DIN Rail Mountable (For the Netbell-2 Controller)	
Accessories	10ft Power Cable/Wago Connectors	
Power Input	12VDC for controller/24VAC for bell (Included)	
Voltage Sensor	On Board	
Temperature Sensor	On Board	
Rechargeable Battery	On Board (For offline time & settings keeping backup up to 7 days)	
Working Temperature	From 0 to +60 Celsius	
Supported Protocols	HTTP/ SMTP/SNTP	

